

# PCS Receive Filter



## 8C9-1880-X60N11

This PCS Band receive filter covers the passband of 1850 - 1910 MHz. It is the perfect compliment to our PCS diplexer.



### Electrical Specifications

Center Frequency	1880 MHz
Passband	1850 - 1910 MHz, minimum
Insertion Loss	$\leq 0.8$ dB @ Passband
Return Loss	$\geq 16$ dB @ Passband
Attenuation	$\geq 60$ dB @ 1930 - 1990 MHz
Connectors	Type N Female in / out
Size	1.75" x 2.75" x 5.5" nominal

**Reactel, Incorporated - Reacting First to Your Filter Requirements**

8031 Cessna Avenue • Gaithersburg, Maryland 20879

Phone: 301-519-3660 • Fax: 301-519-2447 • [reactel@reactel.com](mailto:reactel@reactel.com) • [www.reactel.com](http://www.reactel.com)